

brinno
brilliant innovation

Więcej miejsca, Więcej możliwości

Obudowa wodoodporna do kamer Brinno:
ATH2000

Wykres żywotności baterii



TLC130

TLC130 with ATH2000 est. battery life chart:

TIME LAPSE MODE

Capture interval	Est. TLC130 battery life (days)	Est. ATH2000 battery life (days)	Est. total battery life (days)
ASAP	0.3	1.1	1.4
1 sec	0.3	1.1	1.4
2 sec	0.6	2.3	2.9
5 sec	1.1	4.5	5.6
10 sec	1.4	5.4	6.8
20 sec	1.7	6.6	8.3
30 sec	2.8	11.2	14
1 min	4.1	16.5	20.6
5 min	11.1	44.5	55.6
10 min	12.8	51.1	63.9
1 hr	14.9	59.4	74.3
4 hr	15.5	61.9	77.4
24 hr	16.2	64.8	81

TLC130 with ATH2000 est. battery life chart:

STEP VIDEO MODE

Burst length	Capture interval	Est. TLC130 battery life (days)	Est. ATH2000 battery life (days)	Est. total battery life (days)
3 sec	30 sec	0.2	0.9	1.1
	1 min	1.0	4.0	5
	3 min	1.6	6.2	7.8
	5 min	4.0	15.9	19.9
	10 min	6.6	26.4	33
5 sec	1 min	0.8	3.0	3.8
	3 min	2.2	8.7	10.9
	5 min	3.2	13.0	16.2
	10 min	5.7	22.7	28.4
10 sec	3 min	1.5	5.9	7.4
	5 min	1.9	7.5	9.4
	10 min	4.1	16.6	20.7

TLC120 with ATH2000 est. battery life chart:

TLC120 OPERATED WITH APP

Capture interval	Est. TLC120 battery life (days)	Est. ATH2000 battery life (days)	Est. total battery life (days)
1 sec	1	3	4
2 sec	1	5	6
5 sec	3	11	14
10 sec	5	18	23
20 sec	7	25	32
30 sec	8	30	38
1 min	10	35	45
5 min	12	42	54
10 min	12	43	55
1 hr	12	44	56
4 hr	12	44	56
24 hr	12	44	56

TLC120 with ATH2000 est. battery life chart:

TLC120 OPERATED WITHOUT APP

Capture interval	Est. TLC120 battery life (days)	Est. ATH2000 battery life (days)	Est. total battery life (days)
1 sec	1	3	4
2 sec	1	5	6
5 sec	3	12	15
10 sec	6	21	27
20 sec	9	33	42
30 sec	11	41	52
1 min	15	54	69
5 min	20	72	92
10 min	21	76	97
1 hr	22	78	100
4 hr	22	79	101
24 hr	22	79	101

TLC200Pro with ATH2000 est. battery life chart:

DAYLIGHT

Capture interval	Est. TLC200Pro battery life (days)	Est. ATH2000 battery life (days)	Est. total battery life (days)
ASAP	1	6	7
1 sec	2.3	14	16.3
2 sec	5.6	34	39.6
5 sec	11.5	71	82.5
10 sec	17	104	121
20 sec	25	150	175
30 sec	29	176	205
1 min	35	213	248
5 min	42	256	298
10 min	43	263	306
1 hr	44	269	313
4 hr	44	269	313
24 hr	45	270	315

TLC200Pro with ATH2000 est. battery life chart:

TWILIGHT

Capture interval	Est. TLC200Pro battery life (days)	Est. ATH2000 battery life (days)	Est. total battery life (days)
2 sec	1.6	9	10.6
5 sec	3.2	19	22.2
10 sec	5.9	36	41.9
20 sec	11.5	71	82.5
30 sec	15	95	110
1 min	23	140	163
5 min	38	228	266
10 min	41	247	288
1 hr	44	266	310
4 hr	44	269	313
24 hr	45	270	315

TLC200Pro with ATH2000 est. battery life chart:

NIGHT

Capture interval	Est. TLC200Pro battery life (days)	Est. ATH2000 battery life (days)	Est. total battery life (days)
5 sec	2.3	14	16.3
10 sec	3.5	21	24.5
20 sec	6.5	39	45.5
30 sec	9	55	64
1 min	15	91	106
5 min	32	194	226
10 min	37	226	263
1 hr	43	262	305
4 hr	44	268	312
24 hr	44	269	313

TLC200PRO

TLC200Pro with ATH2000 est. battery life chart:

MOON

Capture interval	Est. TLC200Pro battery life (days)	Est. ATH2000 battery life (days)	Est. total battery life (days)
5 sec	1.5	9	10.5
10 sec	2.2	13	15.2
20 sec	3.5	22	25.5
30 sec	5	32	37
1 min	9	58	67
5 min	25	155	180
10 min	32	197	229
1 hr	42	254	296
4 hr	44	266	310
24 hr	44	269	313